

SYSTEM AND METHOD FOR POWER
LOSS NOTIFICATION

TECHNICAL FIELD OF THE INVENTION

This invention relates generally to power delivery systems, and more particularly to a system and method for power loss notification.

100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237
2238
2239
2240
2241
2242
2243
2244
2245
2246
2247
2248
2249
2250
2251
2252
2253
2254
2255
2256
2257
2258
2259
2260
2261
2262
2263
22

BACKGROUND OF THE INVENTION

Computers often communicate over a network using a modem at a subscriber's location. This modem facilitates the communication of data from the subscriber to a remote location, such as to a central office of a service provider. The modem typically receives power from an external power supply. When the modem loses power, the modem generally informs the central office or other remote location of the power loss. This allows the central office to stop transmitting data to the modem when the modem is unable to receive that data.

Modems often use one or more capacitors to store a voltage charge from the power supply. To determine when a power loss occurs, modems typically use power loss circuitry coupled to the capacitors. The power loss circuitry operates to monitor the voltage between the capacitors and the power supply. When the modem loses power, the power loss circuitry generally detects only the voltage stored in the capacitors. As the capacitors discharge, the charge stored in the capacitors falls below a threshold value, often called a "trip point." The power loss circuitry then generates an output signal indicating that a power loss has occurred. Because the power loss circuitry monitors the level of the voltage charge stored in the capacitors, the circuitry is often referred to as a "level detector."

A problem with this approach is that a relatively long period of time may elapse between the time the modem loses power and the time the power loss circuitry detects the power loss. The power loss circuitry typically must wait for the capacitors to discharge enough voltage before sensing the power loss. This increases the time between the power loss and the detection of the power loss, and this period of time

is often important. For example, the power loss circuitry needs to detect the power loss while enough internal power remains in the modem to transmit a power loss signal to the central office. If too much time elapses before the circuitry
5 detects the power loss, the modem will not have enough power to generate and transmit the power loss signal.

Another problem with this approach is that it typically increases the amount of circuitry used in the modem. For example, this approach often requires the addition of several
10 components, such as additional capacitors coupled to the power supply. These additional components increase the overall cost of the modem and take up space that could be used for other elements in the modem.

SUMMARY OF THE INVENTION

The present invention recognizes a need for an improved system and method for power loss notification, which reduce or eliminate some or all of the problems and disadvantages associated with prior systems and methods.

In one embodiment of the invention, a modem includes communication circuitry operable to facilitate communication over a communication link. The modem also includes at least one capacitor operable to store a voltage when a power supply is supplying at least a threshold voltage to the modem. The modem further includes at least one diode coupled between the power supply and the at least one capacitor. The diode is operable to operate in a forward bias state while the power supply is supplying at least the threshold voltage. In addition, the modem includes a power loss sensor coupled in parallel with the diode and in series with the communication circuitry. The power loss sensor is operable to detect a reverse bias state of the diode and to signal the communication circuitry to communicate a power loss signal over the communication link.

In a particular embodiment of the invention, the power loss sensor comprises a digital detector. The digital detector is operable to detect the presence or absence of a voltage between the diode and the power supply.

In another embodiment of the invention, a method for power loss notification includes receiving at least a threshold voltage from a power supply. The method also includes charging at least one capacitor when the power supply is supplying at least the threshold voltage. The method further includes failing to receive at least the threshold voltage from the power supply, and reverse biasing at least one diode coupled between the power supply and the at least

one capacitor. In addition, the method includes detecting the reverse bias state of the diode.

Numerous technical advantages can be gained through various embodiments of the invention. Various embodiments of the invention may exhibit none, some, or all of the following advantages. For example, in one embodiment of the invention, a modem is provided that quickly identifies when a power loss occurs. The modem may then generate a power loss signal informing a central office or other network element of the power loss. By quickly identifying when the power loss occurs, a shorter period of time may elapse between the time the modem loses power and the time the modem detects the power loss. This helps to reduce or eliminate the likelihood that the modem will be unable to generate and transmit the power loss signal to the central office or other network element.

Some embodiments of the invention also simplify the circuitry used in the modem. For example, in one embodiment, fewer capacitors may be coupled to the power supply and used in the modem. This helps to reduce the size and cost of the modem. Also, the modem is not limited to the use of a "level detector." The modem may, for example, use any digital detector operable to detect the presence or absence of a voltage signal. Although a level detector may still be used to detect a power loss, other less expensive circuits can also be used.

Other technical advantages will be readily apparent to one of skill in the art from the attached figures, description, and claims.

BRIEF DESCRIPTION OF THE DRAWINGS

For a more complete understanding of the present invention and the advantages thereof, reference is now made to the following descriptions taken in connection with the accompanying drawings, in which:

FIGURE 1 is a block diagram illustrating an exemplary communication system constructed according to the teachings of the present invention;

FIGURE 2 is a block diagram illustrating an exemplary modem constructed according to the teachings of the present invention;

FIGURE 3 is a block diagram illustrating an exemplary power loss sensor constructed according to the teachings of the present invention; and

FIGURE 4 is a flow diagram illustrating an exemplary method for power loss notification according to the teachings of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

FIGURE 1 is a block diagram illustrating an exemplary communication system 10 constructed according to the teachings of the present invention. In the illustrated embodiment, system 10 includes one or more host computers 12 and a modem 14 coupled to a power supply 16. A communication link 18 facilitates communication between the modem 14 and other network elements, such as a central office 20 coupled to a network 22. Other embodiments of system 10 may be used without departing from the scope of the present invention.

In general, modem 14 facilitates communication between host 12 and network 22. Modem 14 may, for example, communicate information to and receive information from network 22 through central office 20. Modem 14 also receives power from power supply 16, and modem 14 includes a power loss sensor 24. Power loss sensor 24 detects when modem 14 loses power, or stops receiving at least a threshold voltage, from power supply 16. When power loss sensor 24 detects a power loss, modem 14 communicates a power loss signal to central office 20. In one embodiment, power loss sensor 24 may include a digital detector operable to detect the presence or absence of power from power supply 16.

This invention is described as it relates to the detection of a power loss in modem 14. The invention may also be used to detect a power loss in any other apparatus that receives power from a power supply and attempts to perform an action in response to a power loss. For example, the invention may be used in a laptop computer or a personal digital assistant to signal when a battery power supply is losing power. The invention could also be used in a server computer to signal when the server loses power. In response, the software in the laptop computer, server computer, or

personal digital assistant may store information in a nonvolatile memory and shut down other programs in an orderly fashion. The invention could further be used in a wireless device, such as a mobile telephone or a BLUETOOTH device, to
5 detect a power loss and communicate a "sign-off" signal over a wireless interface.

Host 12 is coupled to modem 14. In this document, the term "couple" refers to any direct or indirect communication between two or more elements, whether or not those elements
10 are in physical contact with one another. Host 12 may execute with any of the well-known MS-DOS, PC-DOS, OS-2, MAC-OS, WINDOWS, UNIX, or other appropriate operating systems. Host 12 may comprise, for example, a desktop computer, a laptop computer, a personal digital assistant, or any other computing
15 or communicating device. In the illustrated embodiment, host 12 includes an input device 26, an output device 28, random access memory (RAM) 30, read-only memory (ROM) 32, CD-ROM, hard drive, or other magnetic or optical storage media 34 or other appropriate volatile or nonvolatile storage and
20 retrieval devices, and a processor 36 having a system clock or other suitable timing device or software. Input device 26 may comprise, for example, a keyboard, mouse, graphics tablet, touch screen, pressure-sensitive pad, joystick, light pen, microphone, or other suitable input device. Output device 28
25 may comprise, for example, a video display, a printer, a disk drive, a plotter, a speaker, or other suitable output device.

Modem 14 is coupled to host 12 and to communication link 18. Modem 14 provides an interface between host 12 and communication link 18. Throughout this document, the term
30 "modem" refers to any combination of hardware, software, and/or firmware operable to facilitate an interface between a communication link and a host device. For example, modem 14

may transport information between host 12 and central office 20. The features and elements of modem 14 may reside externally to host 12, or may be partially or completely integrated into host 12. For example, modem 14 could reside
5 integrally within host 12, may comprise a device card coupled to a bus within host 12, or may comprise a device external to host 12 communicating with host 12 over a communication link 15. In that case, communication link 15 could comprise, for example, a local area network (LAN) such as an Ethernet
10 connection. In addition to providing basic interfacing functions, modem 14 could, in some embodiments, provide routing, bridging, and/or switching functions.

In one embodiment, modem 14 comprises a digital subscriber line (DSL) modem. In this embodiment, modem 14 may
15 implement any of the DSL protocols, including full-rate Asymmetric DSL (ADSL), ADSL Lite, and Very-high-rate DSL (VDSL). Modem 14 may also comprise a cable modem or other suitable communication device. In addition, the invention contemplates other later revisions, modifications,
20 enhancements, or new types of communications techniques. One embodiment of a modem is shown in FIGURE 2, which is described below.

Power supply 16 is coupled to modem 14 and supplies power to modem 14. Power supply 16 may comprise any suitable source
25 of power for modem 14. In one embodiment, power supply 16 comprises a direct current power supply. Power supply 16 may reside externally to modem 14 and/or host 12, or may be partially or completely integrated into modem 14 and/or host 12. For example, power supply 16 could reside within host 12,
30 central office 20, modem 14, or any other suitable location.

Communication link 18 couples modem 14 to central office 20. Communication link 18 facilitates communication between

modem 14 and central office 20. Communication link 18 may comprise any communications medium operable to facilitate communication of analog and/or digital signals using ground-based and/or space-based components. Communication link 18 may, for example, comprise a twisted-pair copper telephone line, a fiber optic line, or a wireless link between modem 14 and central office 20.

In the illustrated embodiment, central office 20 is coupled to communication link 18 and to network 22. Central office 20 facilitates communication between modem 14 and network 22. Network 22 may include any suitable wireline or wireless system that supports communication between network elements using ground-based and/or space-based components. For example, network 22 may be a public switched telephone network (PSTN), an integrated services digital network (ISDN), a local area network (LAN), a wide area network (WAN), a global computer network such as the Internet, or any other communication system or systems at one or more locations.

In the illustrated embodiment, modem 14 includes a power loss sensor 24. Power loss sensor 24 is operable to detect when modem 14 stops receiving at least a threshold voltage from power supply 16. When power loss sensor 24 detects a power loss, power loss sensor 24 causes modem 14 to communicate a power loss signal to central office 20. This informs central office 20 that modem 14 cannot receive information from network 22 because of the power loss. In one embodiment, power loss sensor 24 comprises a digital detector. In this document, the phrase "digital detector" refers to any hardware, software, firmware, or combination thereof operable to detect the presence or absence of a voltage signal from power supply 16. Power loss sensor 24 may, for example, comprise a comparator, a digital gate such as an AND gate, or

a buffer gate. One embodiment of a power loss sensor is shown in FIGURE 3, which is described below.

FIGURE 2 is a block diagram illustrating an exemplary modem 114 constructed according to the teachings of the present invention. Modem 114 may be useful, for example, in system 10 of FIGURE 1. In the illustrated embodiment, modem 114 includes communication circuitry 200, a power supply circuit 202, a power monitor 204, and a power loss sensor 124.

Communication circuitry 200 facilitates communication between one or more hosts 112 and a central office 120 over a communication link 118. Communication circuitry 200 may, for example, receive digital information from host 112 and convert it into analog signals for communication toward a network. Communication circuitry 200 may also receive analog information over communication link 118 and convert it into digital signals for communication to host 112. Communication circuitry 200 may comprise any hardware, software, firmware, or combination thereof operable to facilitate communication over communication link 118. Communication circuitry 118 may, for example, include an analog-to-digital converter, a digital-to-analog converter, and a digital signal processor.

Power supply circuit 202 is coupled to communication circuitry 200 and to a power supply 116. Power supply circuit 202 receives power from power supply 116, generates a voltage signal using the power from power supply 116, and communicates the voltage signal to communication circuitry 200. Power supply circuit 202 may comprise any hardware, software, firmware, or combination thereof operable to receive power and provide a voltage signal to communication circuitry 200. In one embodiment, power supply circuit 202 includes a three amp flyback regulator, such as a LM2585T-ADJ switcher, and a transformer.

Power monitor 204 is coupled to power supply circuit 202 and communication circuitry 200. Power monitor 204 monitors the voltage signal supplied to communication circuitry 200 by power supply circuit 202. When the voltage of the signal supplied to communication circuitry 200 falls outside a threshold range, power monitor 204 generates a reset signal. The reset signal prevents communication circuitry 200 from operating. When the signal supplied to communication circuitry 200 is within the threshold voltage range, power monitor 204 allows communication circuitry 200 to operate. In this manner, power monitor 204 prevents damage to communication circuitry 200 by, for example, an excessive amount of voltage supplied to communication circuitry 200. Power monitor 204 may comprise any hardware, software, firmware, or combination thereof operable to regulate the power supplied to communication circuitry 200. In one embodiment, power monitor 204 comprises a LP2989IM-2.5 Micropower/Low Noise 500 milliamp Ultra-Low Dropout Regulator.

Power loss sensor 124 is coupled to power supply 116, power supply circuit 202, and communication circuitry 200. Power loss sensor 124 monitors the voltage level of the power supplied to modem 114 at a terminal 206. When power supply 116 is supplying power to modem 114, power loss sensor 124 detects a voltage at terminal 206 and allows communication circuitry 200 to continue operating. When modem 114 stops receiving at least a threshold voltage from power supply 116, power loss sensor 124 detects the lack of the threshold voltage at terminal 206 and causes communication circuitry 200 to communicate a power loss signal to central office 120 over communication link 118. Power loss sensor 124 may comprise any hardware, software, firmware or combination thereof operable to detect a power loss at terminal 206. One

embodiment of a power loss sensor is shown in FIGURE 3, which is described below.

To help increase the speed at which power loss sensor 124 detects a loss of power at terminal 206, modem 114 also includes one or more diodes 208 and one or more capacitors 210. Diode 208 is coupled in series between power supply 116 and power supply circuit 202. Diode 208 allows current to flow from terminal 206 to a terminal 212, and diode 208 limits the current flowing from terminal 212 to terminal 206. For example, when the voltage at terminal 206 is above a threshold voltage, such as 0.7 volts, diode 208 operates in a forward bias state, and current may flow through diode 208. When the voltage at terminal 206 drops below the threshold voltage, diode 208 operates in a reverse bias state, and current may not flow through diode 208. In one embodiment, diode 208 is selected to have a current rating high enough to withstand the ordinary current flowing through diode 208 when power supply 116 is supplying power to modem 114. Also, diode 208 may be selected to withstand surge currents experienced in modem 114, such as when modem 114 is coupled to power supply 116. In a particular embodiment, modem 114 also includes a resistor 214 coupled in series with diode 208. Resistor 214 helps to limit the surge current experienced by diode 208 in modem 114. In addition, diode 208 may be selected to withstand the back bias voltage when modem 114 loses power from power supply 116. When modem 114 loses a sufficient amount of power, a higher voltage may exist at terminal 212 than at terminal 206, and a back bias voltage exists across diode 208. Selecting a diode 208 having suitable current and back bias voltage ratings may help to ensure proper operation of modem 114. Diode 208 may comprise any suitable diode or diodes, such as a silicon diode or a Schottky diode. In one embodiment, multiple diodes 208

may be used in modem 114. Any combination of diodes 208 may be selected to vary the threshold voltage at which diodes 208 reverse bias and power loss sensor 124 detects the power loss.

One or more capacitors 210 are coupled between diode 208 and, for example, a ground 216. Capacitors 210 receive and store a voltage charge when power supply 116 supplies sufficient power to modem 114 to forward bias diode 208. Capacitors 210 may comprise any suitable capacitor or capacitors operable to store sufficient voltage to allow communication circuitry 200 to continue operating until a power loss notification signal can be communicated to central office 120. For example, capacitors 210 may comprise two 1,000 microfarad capacitors and one forty-seven microfarad capacitor coupled in parallel.

In one aspect of operation, when power supply 116 supplies power to modem 114, at least a threshold voltage appears at terminal 206, and power loss sensor 124 does not detect a power loss in modem 114. Also, when power supply 116 provides power to modem 114, diode 208 is forward biased, and capacitors 210 store a voltage charge. When power supply 116 stops supplying at least a threshold voltage to modem 114, the voltage stored in capacitors 210 appears as a voltage at terminal 212. The lack of a voltage at terminal 206, coupled with the voltage at terminal 212, reverse biases diode 208. This produces a zero or near-zero voltage at terminal 206. Power loss sensor 124 detects the reverse bias state of diode 208 and signals communication circuitry 200 to communicate a power loss signal to central office 120.

The use of diode 208 and capacitor 210 in modem 114 helps to increase the speed at which a zero or near-zero voltage signal appears at terminal 206. This also increases the speed at which power loss sensor 124 detects a power loss in modem

114. By detecting the loss of power in modem 114 in less time, communication circuitry 200 has more time to communicate the power loss signal to central office 120. This helps to decrease the likelihood that communication circuitry 200 will
5 lose power before generating and communicating the power loss signal to central office 120.

FIGURE 3 is a block diagram illustrating an exemplary power loss sensor 224 constructed according to the teachings of the present invention. Power loss sensor 224 may be
10 useful, for example, in modem 114 of FIGURE 2. In the illustrated embodiment, power loss sensor 224 includes two comparators 300a and 300b, resistors 302-324, capacitors 326-330, a zener diode 332, and a transistor 334. Other embodiments of power loss sensor 224 may be used without
15 departing from the scope of the present invention.

Each comparator 300 is operable to receive a first input 336 and a second input 338. Each comparator 300 is also operable to receive power through a terminal 340, and each comparator 300 is coupled to a ground through a terminal 342.
20 Comparator 300 is operable to compare the input signals 336 and 338 and generate an output signal 344 based on the comparison. Comparator 300 may comprise any hardware, software, firmware or combination thereof operable to receive and compare input signals. In one embodiment, comparators 300
25 comprise a LM2903 Low Power, Low Offset Voltage, Dual Comparator.

In the illustrated embodiment, resistor 320 is coupled to a voltage source 354. In one embodiment, voltage source 354 comprises a 3.3 volt direct current voltage signal. Component
30 values for resistors 302-324 and capacitors 326-330 may be selected to provide any desired functionality of power loss sensor 224. In a particular embodiment, resistors 302 and 304

each comprise a 4.99 kilo-ohm resistor; resistors 306 and 308 each comprise a one kilo-ohm resistor; resistor 310 comprises a ten ohm resistor; resistor 312 comprises a two kilo-ohm resistor; resistors 314, 316, and 318 each comprise a 25.5 kilo-ohm resistor; resistors 320 and 322 each comprise a 7.5 kilo-ohm resistor; resistor 324 comprises a ten kilo-ohm resistor; capacitor 326 comprises a one microfarad capacitor; and capacitors 328 and 330 each comprise a 2.2 microfarad capacitor. Other component values may be selected without departing from the scope of the present invention.

Zener diode 332 may comprise any suitable diode. In one embodiment, zener diode 332 comprises a TL431CPK adjustable precision shunt regulator. Transistor 334 may comprise any suitable transistor. In one embodiment, transistor 334 comprises a NPN transistor. In a particular embodiment, transistor 334 comprises a MMBT2222 NPN transistor. In the illustrated embodiment, transistor 334 includes a collector 350 coupled to a voltage source 346 and a base 352 coupled to comparator 300a. In one embodiment, voltage source 346 comprises a 3.3 volt direct current voltage signal.

In one aspect of operation, when modem 114 is receiving at least a threshold voltage from power supply 116, the voltage at terminal 206 exceeds the voltage at terminal 212. This may, for example, be due to the voltage drop across diode 208. Comparator 300a receives at least a portion of the voltage at terminal 212 as input signal 336a and at least a portion of the voltage at terminal 206 as input signal 338a. Comparator 300a compares the signals 336a and 338a and, because the voltage at terminal 206 exceeds the voltage at terminal 212, outputs a low voltage signal 344a. The low voltage signal is communicated to base 352 of transistor 334, which signals communication circuitry 200 to operate normally.

When modem 114 stops receiving at least a threshold voltage from power supply 116, diode 208 begins operating in a reverse bias state. The voltage at terminal 212 exceeds the voltage at terminal 206 because, for example, capacitors 210
5 may contain a voltage charge. Comparator 300a receives at least a portion of the voltage at terminal 212 as input signal 336a and at least a portion of the voltage at terminal 206 as input signal 338a. Comparator 300a compares the signals 336a and 338a and, because the voltage at terminal 212 exceeds the
10 voltage at terminal 206, outputs a high voltage signal 344a. The high voltage signal 344a is communicated to base 352 of transistor 334, which signals communication circuitry 200 to communicate a power loss signal.

In the illustrated embodiment, the output signal 344b of
15 comparator 300b is communicated to power supply circuit 202. Power supply circuit 202 may use output signal 344b in providing power to communication circuitry 200. For example, in one embodiment, power supply circuit 202 includes a three amp flyback regulator, such as a LM2585T-ADJ switcher, and
20 output signal 344b is used as a compensation pin voltage in the flyback regulator.

Although FIGURE 3 illustrates one embodiment of power loss sensor 224, numerous changes may be made without departing from the scope of the present invention. For
25 example, the arrangement and values of components in power loss sensor 224 is for illustration only. Other arrangements and/or component values may be used without departing from the scope of the present invention.

FIGURE 4 is a flow diagram illustrating an exemplary
30 method 400 for power loss notification according to the teachings of the present invention. Although method 400 is

described below as it relates to modem 114, the same or similar method may be used by modem 14 of system 10.

Modem 114 receives power at step 402. This may include, for example, modem 114 receiving power from power supply 116.

5 Modem 114 charges one or more capacitors 210 at step 404. This may include, for example, capacitors 210 charging when modem 114 is receiving power from power supply 116.

Modem 114 loses power at step 406. This may include, for example, modem 114 failing to receive at least a threshold
10 voltage from power supply 116. Modem 114 reverse biases diode 208 at step 408. The lack of at least a threshold voltage at terminal 206 caused by the loss of power, coupled with the voltage at terminal 212 from the stored voltage in capacitors 210, reverse biases diode 208. Modem 114 detects the reverse
15 bias state of diode 208 at step 410. This may include, for example, power loss sensor 124 detecting the absence of a voltage between power supply 116 and diode 208. After detecting the absence of a voltage, power loss sensor 124 may take any suitable corrective action, such as instructing
20 communication circuitry 200 to communicate a power loss signal to central office 120.

Although the present invention has been described in several embodiments, a myriad of changes, variations, alterations, transformations, and modifications may be
25 suggested to one skilled in the art, and it is intended that the present invention encompass such changes, variations, alterations, transformations, and modifications as fall within the spirit and scope of the appended claims.